



Test Report: PV-ML24-40

20A MPPT controller

■ DESIGN VERIFY TEST

Output Function Test

Input Function Test

Protection Function Test

Control Function Test

■ SAFETY & E.M.C. TEST

Safety Test

E.M.C. Test

■ RELIABILITY TEST

ENVIRONMENT TEST

■ DESIGN VERIFY TEST

OUTPUT FUNCTION TEST

| NO | TEST ITEM | SPECIFICATION | TEST CONDITION | RESULT |
|----|-----------------------------------|----------------------------------|---|-------------------|
| 1 | BOOST CHARGE VOLTAGE (default) | 14.4V(12V BAT) 28.8V(24V BAT) | I/P : NONE O/P : BAT LOAD Ta : 25°C | 14.317V 28.74V |
| 2 | FLOAT CHARGE VOLTAGE (default) | 13.8V 27.6V | I/P : NONE O/P : BAT LOAD Ta : 25°C | 13.78V 27.52V |
| 2 | CHARGING CURRENT | 40A | I/P: BAT O/P:BAT LOAD Ta:25°C | 39.52A |

INPUT FUNCTION TEST

| NO | TEST ITEM | SPECIFICATION | TEST CONDITION | RESULT |
|----|---------------------------|---------------|--|------------|
| 1 | INPUT VOLTAGE RANGE | ~100V | I/P: Testing O/P: :NO LOAD Ta:25°C | 3.85V~121V |
| 2 | EFFICIENCY (TYP) | 98% | I/P: Testing O/P:NO LOAD Ta:25°C | 98.22% |
| 3 | MPPT EFFICIENCY (TYP) | 99% | I/P : PV O/P : BAT LOAD Ta : 25°C | 99.96% |
| 4 | NO LOAD POWER CONSUMPTION | <1.2W | I/P : 24V O/P : NO LOAD Ta : 25°C | 0.1673W |

PROTECTION FUNCTION TEST

| NO | TEST ITEM | SPECIFICATION | TEST CONDITION | RESULT |
|----|---------------------------------|---|---|--------|
| 1 | INPUT OVER VOLTAGE | >150V | I/P: Testing O/P: Battery Ta:25°C | 121.2V |
| 2 | OUTPUT OVER VOLTAGE | Shut off o/p voltage, clamping by zener diode | O/P: Testing Ta:25°C | 42.7V |
| 3 | OVER-DISCHARGE VOLTAGE | 11.1V | I/P: Testing O/P: Battery Ta:25°C | 11.1V |
| 4 | OVER-DISCHARGE RECOVERY VOLTAGE | 12.6V | I/P: NC O/P: Testing Ta:25°C | 12.62V |

| | | | | |
|---|---------------------------------------|---------------------------|---|-----------|
| 5 | OLP | >110% | I/P: Testing O/P: Testing Ta:25°C | 23.5A |
| 6 | SHORT | Shut down | I/P: PV O/P: Testing Ta:25°C | TEST : OK |
| 7 | BATTERY REVERSE CONNECTION | Shut down, Auto recovery | I/P: NC O/P: Battery Ta:25°C | TEST : OK |
| 8 | PHOTOVOLTAIC INPUT REVERSE-CONNECTION | Shut down,, Auto recovery | I/P: PV O/P: NC Ta:25°C | TEST : OK |

CONTROL FUNCTION TEST

| NO | TEST ITEM | SPECIFICATION | RESULT | |
|----|--------------------|-----------------------------------|--|---|
| 1 | BUTTON | UP | Page up; increase the parameter value in setting TEST : OK | |
| | | DOWN | Page down; decrease the parameter value in setting TEST : OK | |
| | | RETURN | Return to previous menu TEST : OK | |
| | | CONFIRM | Enter into sub-menu; set/ saveTurn on/off loads TEST : OK | |
| 2 | LOAD MODEL SETTING | Sole light control | TEST : OK | |
| | | Light control + time control mode | TEST : OK | |
| | | Manual mode | TEST : OK | |
| | | Debugging mode | TEST : OK | |
| | | Normal on mode | TEST : OK | |
| | BATTERY TYPE | Sealed | System voltage12/24 Auto 1. Equalizing charging voltage 2. Boost charging voltage 3. Floating charging voltage 4. Over-discharge recovery voltage 5. Over-discharge voltage | TEST : OK 1.14.6V 2.14.4V 3.13.8V 4.12.6V 5..11.1V |
| | | Gel | System voltage12/24 Auto 1. Boost charging voltage 2. Floating charging voltage 3. Over-discharge recovery voltage 4. Over-discharge voltage | TEST : OK 1.14.2V 2.13.8V 3.12.6V 4.11.1V |
| | | Li | System voltage12/24 Auto | TEST : OK |
| | | | | |

| | | | | |
|--|--|--|---|---|
| | | | 1. Boost charging voltage 2. Over-discharge recovery voltage 3. Over-discharge voltage | 1.14.4V 2.12.6V 3.11.1V |
| | | | Flooded System voltage12/24 Auto 1. Equalizing charging voltage 2. Boost charging voltage 3. Floating charging voltage 4. Over-discharge recovery voltage 5. Over-discharge voltage | TEST : OK 1.14.8V 2.14.6V 3.13.8V 4.12.6V 5..11.1V |
| | | | User System voltage12/24 Auto 1. Equalizing charging voltage 2. Boost charging voltage 3. Floating charging voltage 4. Over-discharge recovery voltage 5. Over-discharge voltage | TEST : OK Can set the voltage range: 9-17V |

■ SAFETY& E.M.C. TEST

SAFETY TEST

| NO | TEST ITEM | SPECIFICATION | TEST CONDITION | RESULT |
|----|-------------------|--|--|-----------|
| 1 | WITHSTAND VOLTAGE | DC-FG: 1.5KVAC/min PV-FG :1.5KVAC/min | DC-FG: 1.5KVAC/min PV-FG :1.5KVAC/min | NO DAMAGE |

E.M.C TEST

| NO | TEST ITEM | SPECIFICATION | TEST CONDITION | RESULT |
|----|-----------|---|--|-----------|
| 1 | CONDUCTED | BS EN/EN61000-6-3 Class A | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| 2. | RADIATION | BS EN/EN61000-6-4 Class B | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| 3 | E.S.D | BS EN/EN61000-4-2 ■ MEDICAL AIR : 8KV / Contact : 4KV | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| 4 | RF | BS EN/EN61000-4-3 | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |

| | | | | |
|--|-------------------------|-------------------|--|-----------|
| 5 | EFT | BS EN/EN61000-4-4 | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| 6 | SURGE | BS EN/EN61000-4-5 | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| 7 | CONDUCTED | BS EN/EN61000-4-6 | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| 8 | Magnetic field immunity | BS EN/EN61000-4-8 | I/P : PV O/P : FULL LOAD Ta : 25°C | TEST : OK |
| <p>Test by certified Lab & Test Report Prepare</p> <p>Any contradictions of the test results, please refer to the latest EMC test report</p> | | | | |

■ RELIABILITY TEST

ENVIRONMENT TEST

| NO | TEST ITEM | SPECIFICATION | TEST CONDITION | RESULT | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|----|----------------------------|--|---|--------|----------|-----------------------------|---------------------------|---|----------|------|------|---|---------------|------|----|---|---------------|------|------|---|---------------|------|----|---|---------------|------|------|---|------------|------|------|---|------------|------|------|---|---------------|------|------|---|-------------|------|-------|----|----------------------------|------|------|----|--------|------|------|----|--------------|------|------|----|-----|------|------|----|-----------------|------|------|----|------------|------|------|----|------------------|------|----|----|-------------|------|------|----|------------|------|------|----|-----------------|------|------|----|-------------------|----|------|--|
| 1 | TEMPERATURE RISE TEST | MODEL : PV-ML48-60 1. ROOM AMBIENT BURN-IN : 2 HRS I/P : 150VDC O/P : FULL LOAD Ta= 23.8 °C 2. HIGH AMBIENT BURN-IN : 2 HRS I/P : 150VDC O/P : FULL LOAD Ta= 45.2 °C | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | <table border="1"> <thead> <tr> <th>NO</th> <th>Position</th> <th>ROOM AMBIENT Ta= 23.8 °C</th> <th>HIGH AMBIENT Ta=45.2°C</th> </tr> </thead> <tbody> <tr><td>1</td><td>Varistor</td><td>50.1</td><td>71.1</td></tr> <tr><td>2</td><td>Capacitor C24</td><td>24.8</td><td>46</td></tr> <tr><td>3</td><td>Capacitor C28</td><td>24.6</td><td>45.4</td></tr> <tr><td>4</td><td>Capacitor C33</td><td>24.1</td><td>44</td></tr> <tr><td>5</td><td>Capacitor C34</td><td>26.5</td><td>47.3</td></tr> <tr><td>6</td><td>MOSFET Q12</td><td>60.2</td><td>80.6</td></tr> <tr><td>7</td><td>MOSFET Q15</td><td>56.9</td><td>78.2</td></tr> <tr><td>8</td><td>Switch button</td><td>33.1</td><td>54.5</td></tr> <tr><td>9</td><td>Inductor L1</td><td>81.2</td><td>101.7</td></tr> <tr><td>10</td><td>Winding of the inductor L1</td><td>67.1</td><td>87.7</td></tr> <tr><td>11</td><td>E-Cap.</td><td>64.8</td><td>86.3</td></tr> <tr><td>12</td><td>DIODE Module</td><td>54.4</td><td>75.7</td></tr> <tr><td>13</td><td>PCB</td><td>49.4</td><td>70.4</td></tr> <tr><td>14</td><td>Input connector</td><td>41.5</td><td>62.9</td></tr> <tr><td>15</td><td>Input wire</td><td>40.1</td><td>61.9</td></tr> <tr><td>16</td><td>output connector</td><td>32.6</td><td>54</td></tr> <tr><td>17</td><td>output wire</td><td>33.7</td><td>54.4</td></tr> <tr><td>18</td><td>LED screen</td><td>36.4</td><td>57.4</td></tr> <tr><td>19</td><td>Plastic buttons</td><td>23.1</td><td>44.2</td></tr> <tr><td>20</td><td>Plastic enclosure</td><td>23</td><td>43.6</td></tr> </tbody> </table> | NO | Position | ROOM AMBIENT Ta= 23.8 °C | HIGH AMBIENT Ta=45.2°C | 1 | Varistor | 50.1 | 71.1 | 2 | Capacitor C24 | 24.8 | 46 | 3 | Capacitor C28 | 24.6 | 45.4 | 4 | Capacitor C33 | 24.1 | 44 | 5 | Capacitor C34 | 26.5 | 47.3 | 6 | MOSFET Q12 | 60.2 | 80.6 | 7 | MOSFET Q15 | 56.9 | 78.2 | 8 | Switch button | 33.1 | 54.5 | 9 | Inductor L1 | 81.2 | 101.7 | 10 | Winding of the inductor L1 | 67.1 | 87.7 | 11 | E-Cap. | 64.8 | 86.3 | 12 | DIODE Module | 54.4 | 75.7 | 13 | PCB | 49.4 | 70.4 | 14 | Input connector | 41.5 | 62.9 | 15 | Input wire | 40.1 | 61.9 | 16 | output connector | 32.6 | 54 | 17 | output wire | 33.7 | 54.4 | 18 | LED screen | 36.4 | 57.4 | 19 | Plastic buttons | 23.1 | 44.2 | 20 | Plastic enclosure | 23 | 43.6 | |
| NO | Position | ROOM AMBIENT Ta= 23.8 °C | HIGH AMBIENT Ta=45.2°C | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1 | Varistor | 50.1 | 71.1 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 2 | Capacitor C24 | 24.8 | 46 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 3 | Capacitor C28 | 24.6 | 45.4 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 4 | Capacitor C33 | 24.1 | 44 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 5 | Capacitor C34 | 26.5 | 47.3 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 6 | MOSFET Q12 | 60.2 | 80.6 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 7 | MOSFET Q15 | 56.9 | 78.2 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 8 | Switch button | 33.1 | 54.5 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 9 | Inductor L1 | 81.2 | 101.7 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 10 | Winding of the inductor L1 | 67.1 | 87.7 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 11 | E-Cap. | 64.8 | 86.3 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 12 | DIODE Module | 54.4 | 75.7 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 13 | PCB | 49.4 | 70.4 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 14 | Input connector | 41.5 | 62.9 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 15 | Input wire | 40.1 | 61.9 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 16 | output connector | 32.6 | 54 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 17 | output wire | 33.7 | 54.4 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 18 | LED screen | 36.4 | 57.4 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 19 | Plastic buttons | 23.1 | 44.2 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 20 | Plastic enclosure | 23 | 43.6 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |



MPPT controller

PV-ML24-40 series

| | | | | |
|---|---------------------------------|---|---|-----------|
| 2 | HIGH TEMPERATURE | NO DAMAGE 1 HOUR | I/P : BAT O/P : FULL LOAD Ta : 50°C | TEST : OK |
| 3 | LOW TEMPERATURE TURN ON TEST | TURN ON AFTER 2 HOUR | I/P : BAT O/P : 100%LOAD Ta= -10°C | TEST : OK |
| 4 | VIBRATION TEST | 10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes | 1 Carton & 1 Set (1) Waveform : Sine Wave (2) Frequency : 10~500Hz (3) Sweep Time : 10min/sweep cycle (4) Acceleration : 3G (5) Test Time : 180min in each axis (X.Y.Z) (6) Ta : 25°C | TEST : OK |

| TEST RESULT | TESTER | REVIEW | APPROVAL |
|-------------|--------|--------|----------|
| PASS | Jinkj | | Chenhm |

2020.10.1 TAG-QA-009